

Saving / Loading

New show	SETUP <View Settings> <New Show>
Save show	SETUP <View Settings> <Save Show>
Load show	SETUP <View Settings> <Load Show>
Save settings	SETUP <Save Setting>
Load settings	SETUP <Import Settings>
Save partial show	SETUP [SHIFT + Export Show]
Merge in show	SETUP [SHIFT + Import Show]
Load archive	SETUP [SHIFT + Load Backup]
Export patch list	PATCH <View Chans> <Export Patch>
Reset console	SETUP, <SHIFT + QUIT>

Patching

Select head for patching	PATCH <Choose Head>
Patch 1 head, next free address	1 <Patch It>
Patch 5 heads, next free address	5 <Patch It>
Patch 1 head at uni 1 address 1	1@1-1 <Patch It>
Patch 5 heads at uni 2 address 1	1@2-1 <Patch It>
Patch 5 heads with offset 20	5/20 <Patch It>
Patch after uni 3 address 50	5@+3-50 <Patch It>
Reselect head	Cursor to head [SHIFT + Choose Head]
Edit patched head	Cursor to head [SHIFT + Edit Head]

Select Heads

Select head 1	1 @@
Select heads 1 to 4	1 THRU 4 @@
Select heads 1 to 10, not 5	1 THRU 10 - 5 @@
Deselect all heads	0 @@
Reselect last heads after CLEAR	ALL
Select Group 1	1 * *
Select Groups 1 to 4	1 THRU 4 * *
Sub select 1 st head	1 NEXT HEAD
Sub select 1 st and 2 nd head in group	1 + 2 NEXT HEAD
Sub select 3 rd 4 th and 5 th head	3 THRU 5 NEXT HEAD
Select all heads using palette	ALL + <Palette entry>
Select heads active in Playback	ALL + S
Select heads above 20% intensity	20 [ALL + INT]

Lamp On / Lamp Off / Reset

Lamp On entire rig	MACRO <Lamp on all>
Lamp Off entire rig	MACRO <Lamp off all>
Lamp On selected heads	SHIFT + LOCATE
Lamp Off selected heads	CTRL + SHIFT + LOCATE
Reset selected heads	CTRL + LOCATE

Setting Intensities

Set head 1 to 100%	1 @ FULL (Also 1 FULL)
Set head 1 to 50%	1 @ 50 ENTER
Set heads 1 to 4 to 100%	1 THRU 4 @ FULL
Set head 1 +10%	1 @ + 10 ENTER
Set head 1 -1%	1 @ - 01 ENTER
Set head 1 to 50% time 3 secs	1 @ 50 / 3 ENTER
Heads 1 to 10, 100% split delays 4s to 1s, 1s fade	1 > 10 @ FULL / 4 > 0 / 1
PC Keyboard THRU = '>' FULL = '#'	

FX

Add FX	Select heads, FX <ADD FX>
Convert chase to FX	CUE STK [SHIFT + Make FX]
Force Cue to have no FX	Select heads <Add FX 0 Size>

Playback

Step through Cue Stack	>
Step back up Cue Stack	(also SHIFT + >)
Go to next step without time	>>
Go back a step without time	<<
Reassert Playback	S + <FLASH button>
Take manual control of Playback	S + <move manual fader>
Change chase / FX speed live	S + <turn encoder X>
Goto Cue ID 2	S 2 ENTER
Goto on current Cue Stack	2 <Master GO>
Release Playback with 3 sec time	S 3 REL
Release all Playbacks	SHIFT + REL
Release all test Playbacks/Cues/Cue Stacks	CTRL + REL
Enter/exit Blind with 3 sec time	3 BLIND
Make Cue Stack default all pages	Change to Page 1, PLAYBACK, <Default Cue Stack>

Loading Values into the Programmer

Default all attribs	Select heads, LOCATE
Default position attribs	Select heads [POS + LOCATE]
Default colour attribs	Select heads [COLOR + LOCATE]
Default beam attribs	Select heads [BEAM + LOCATE]
Default intensity attribs	Select heads [INT + LOCATE]
Make active all attribs	Select heads, [* + SET]
Make active pos attribs	Select heads, [POS + SET]
Make active colour attribs	Select heads, [COLOR + SET]
Make active beam attribs	Select heads, [BEAM + SET]
Make active int attribs	Select heads, [INT + SET]
Load Cue from Playback	INC S
Load Cue ID 2	2 INC S
Load Cue at 40%	@ 40 INC S
Load Cue at current level	@ INC S
Load entire state of Cue Stack	ALL + INCLUDE
Load selected heads	[SHIFT + INC] <Selected Only> S
Load from DMX	Select heads, [CTRL + INC] ENTER
Snapshot output cues	PROG, <Snapshot>

MagicQ Short Cuts

Removing Values from the Programmer

Clear all values	CLEAR
Clear with 3 sec time	3 CLEAR
Clear selected heads	Select heads, SHIFT + CLEAR
Clear to 0 vals	CTRL + CLEAR
Remove attrib	REMOVE + <turn encoder>
Remove attrib	<soft button> + REMOVE
Remove position attribs	POS + REMOVE
Remove colour attribs	COLOR + REMOVE
Remove beam attribs	BEAM + REMOVE
Remove intensity attribs	INT + REMOVE

Recording Cues

Record Cue on Playback	RECORD S
Record Cue ID 2.5	2.5 RECORD S
Record Cue to current Playback	RECORD ENTER
Record to Playback 2	RECORD 2 ENTER
Record to Cue ID 2.5 Playback 2	RECORD 2 / 2.5 ENTER
Record sel heads only	[SHIFT + RECORD] <Sel Only> S
Record sel attribs	[SHIFT + RECORD], select attribs, S
Record merge	'+' + RECORD
Record remove	'-' + RECORD
Record entire state of programmer	ALL + RECORD
Record snapshot of console	THRU + RECORD

Editing Cues

Edit in Programmer	INC <S>, make change, UPDATE
Record merge	Change vals in Prog, [S + RECORD]
Rec merge all Cue Stack	['+' + REC] S
Rec remove all Cue Stack	['-' + REC] S
Remove Cue Stack	REMOVE S
Remove Cue ID 2.5	REMOVE 2.5 S
Copy Playback	COPY source S dest S
Copy Playback unlinked	[SHIFT + COPY] source S dest S

Palettes

Record Palette	Select heads, REC, <palette>
Re-record Palette	Select heads, REC, <palette>
Name Palette	Type name, SET, <palette>
Name Palette (no keyboard)	SET SET, type name, <palette>
Edit Palette	Select heads, INC, <palette>, make changes, UPDATE
Play Palette with 3 secs	3 <palette>
Play Palette with 3 secs fanned	3 * <palette>
Play Palette fan fade 0 to 3s	0 THRU 3 <palette>
Play fan delay 0 to 3s, 1s fade	0 THRU 3 / 1 <palette>
Copy Palettes to Playback	[SHIFT + cursor] to select palettes, COPY S

Information Windows

Output Info Window	CTRL + OUT
Programmer Info Window	CTRL + PROG
Cue Stack Info Window	CTRL + CUE STACK

Wing / Keypad short cuts

Select position palette	POS + S
Select colour palette	COLOR + S
Select beam palette	BEAM + S
Select position palette 4	POS 4 ENTER
Select colour palette 5	COLOR 5 ENTER
Select position 4 time 5 secs	POS 4 / 5 ENTER
Select position 4 time 5 secs fan	POS 4 / 5 * ENTER
Default intensity attribs	ALL + LOCATE
Make active intensity attribs	ALL + SET
Remove intensity attribs	ALL + REMOVE

Console

Start up	Start button on rear
Shut down	SETUP, QUIT
Soft reset	SETUP, [SHIFT + QUIT]
Calibrate touch screen	SETUP, <View Settings> <Cal Touch>
Hard reset	Hold rear reset button 5 seconds
Hard power off	Hold rear reset button 15 seconds
Lock/unlock console	CTRL + <SOFT button Encoder A>
Console lights on/off	CTRL + <SOFT button Encoder B>
Enter/exit test mode	SHIFT + SHIFT

Cue Stack Macros

Activate Playback	A <Playback no>
Run Keyboard Macro	B <Macro no>
Release Playback	R <Playback no>
Activate Playback 100%	T <Playback no>
Release Playback 0%	U <Playback no>
Go Playback	G <Playback no>
Stop Playback	S <Playback no>
Choose Playback	C <Playback no>
Run Cue Stack	E <Cue Stack id>
Stop Cue Stack	F <Cue Stack id>
Set level last Cue Stack activated	K <Level>
Set level current Playback	L <Level>
Set level of this Playback	M <Level>
Jump to Cue id current Playback	J <Cue Id>
Change Page	P <Page no> (0 is next)
Open view (window layout)	V <View no>
Enable/disable time code gen	W <Enable> (1 enable, 0 dis)
Set current time code gen	Q <Time code>

Activate Playback 18 on wing 1	A1-18
Go on Playbacks 3 to 5	G3THRU5
Set the level of Playback 6 to 60%	C6L60